



# G-STAR COMMUNICATIONS LTD.

www.gstarcom.net



## GP-98-SP

### P-Switch

<b>Receiver Power Switch Model Name</b>		<b>GP-98-SP/GP-96-SP/GP-94-SP</b>			
<b>NO. of Inputs</b>	<b>SAT/IF</b>		<b>8</b>		
	<b>Terr.</b>		<b>1</b>		
<b>NO. of Outputs</b>	<b>Receiver Users</b>		<b>8/6/4</b>		
<b>Frequency</b>	<b>SAT/IF</b>		<b>950-2250 MHz</b>		
	<b>Terr.</b>		<b>47-862 MHz</b>		
<b>Max Output Power Level</b>	<b>SAT/IF</b>		<b>105 dBμV</b>		
<b>Output Loss</b>	<b>Receiver</b>	<b>SAT/IF</b>		<b>0-3 dB</b>	<b>0-3 dB</b>
		<b>Terr</b>	<b>Passive</b>	<b>20 dB</b>	<b>20 dB</b>
<b>Isolation</b>	<b>Sat / Terr.</b>		<b>30 dB</b>		
	<b>Terr. / Sat</b>		<b>25 dB</b>		
	<b>Sat / Sat</b>		<b>30 dB</b>		
	<b>Vert./Hor.</b>		<b>30 dB</b>		
<b>Power Source</b>	<b>Satellite Receiver</b>				
<b>Dimension</b>	<b>24.8 x 7.6 x 4.4cm</b>				
<b>Weight</b>	<b>332g</b>				